



**Anslut GOLD till Swegon  
INSIDE Cloud**



# Vilka produkter är INSIDE Ready?

## **GOLD-aggregat producerade vecka 22, 2023 eller senare.**

- Mjukvaruversion 2.41 eller senare
- Certifikat installerade i produktion på produkter producerade från vecka 22, 2023

## **Retrofit**

- Mjukvaruversion 2.42 eller senare
- GOLD version E / F




**Hur kopplas ett GOLD-  
aggregat upp?**

# Koppla upp GOLD till internet


## 1. Ethernet-anslutning

Anslut ena änden av nätverkskabeln till anläggningens befintliga nätverk och den andra änden av kabeln till luftbehandlingsaggregatet (IQLogic).




## 2. Mobilt nätverk

Använd en 4G-router med SIM-kort, speciellt utvecklat för detta ändamål.




# Aktivera Swegon INSIDE på HMI/Web



Gå till "Kommunikation"

Kontrollera att följande fält är korrekt ifyllda:

- IP-adress, Nätmask, Standard gateway, Primär DNS
- Produktens serienummer



# Skapa ett konto

- Gå till [Swegons hemsida](#)
  - Support & software → Uppkopplade produkter
- 1 Begär åtkomst till INSIDE Portal
- 2 Fyll i formuläret och klicka “Skicka”
  - Invänta sedan mail med inbjudan till INSIDE Portal

Kom igång!

1

1. Begär åtkomst till INSIDE Portal	▼
2. Lägg till produkter i INSIDE Portal/Gör din produkt INSIDE Ready (endast för retrofit)	▼
3. Gå till INSIDE Portal	▼

Kom igång!

1. Begär tillgång till INSIDE Portal

Ange uppgifterna nedan för att begära ett konto.

Om du redan har ett konto och vill lägga till en ny produkt eller byggnad, kontakta [digitalservices@swegon.com](mailto:digitalservices@swegon.com)

**Kontoinformation**

Email (används som användarnamn)\*

Förnamn\*

Efternamn\*

Företag\*

**Byggnads- och produktinformation**

Välj produkt\*  
Välj ▼

Produktens serienummer\*

Byggnadens namn\*

Byggnadens adress\*

Ort\*

Land\*  
Välj ▼

Din integritet är viktig för oss. Swegon använder dina uppgifter till att förse dig med information om den begärda tjänsten. Du kan avregistrera dig från denna kommunikation när som helst. För mer information, se vår integritetspolicy.

skyddas av reCAPTCHA  
inmatning - Vikor


SKICKA

2

# 1. Logga in på INSIDE Portal

## Swegon INSIDE Portal

- <https://inside.swegon.com>



The screenshot shows the Swegon INSIDE Portal login interface. On the left, there is a decorative graphic of overlapping semi-circles in various colors (orange, yellow, green, blue, purple) and the text "Feel good **inside**". On the right, the login form is titled "Welcome to Swegon INSIDE". It includes a message: "You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account." Below this are input fields for "Email" and "Password". There is a checkbox for "Remember Login" and a link for "Forgot your password?". A green "Log in" button is positioned below the form. Below the button, there is an "OR" separator and a button labeled "Login as internal provider" with a small green leaf icon. At the bottom, there is a section titled "Don't have an account?" with a link "Sign up here".

Feel good **inside**

**Welcome to Swegon INSIDE**


You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account.

Email  
Password

Remember Login    [Forgot your password?](#)

**Log in**

OR

 Login as internal provider

**Don't have an account?**  
[Sign up here](#)

## 2. Gå till byggnadssidan

The screenshot displays the Swegon user interface for an organization. The breadcrumb navigation at the top reads "Home > Organisations > Company Name". A "GO BACK" button is on the left, and an "EDIT ORGANISATION" button is on the right. The main heading is "Company Name".

The "Buildings" section is highlighted with a red circle. It contains a search bar labeled "Search for building name" with a magnifying glass icon. Below the search bar is a table with the following data:


Name	City	Country	Number of products	Role
Head Office	Stockholm	Sweden	0	Organisation Admin

At the bottom of the table, there is a pagination control: "Rows per page: 100" and "1-1 of 1". Below the table are two expandable sections: "Organisation administrators" and "App users".

The left sidebar contains several icons: a menu icon, a user icon, a building icon, a search icon, a notification icon, and a bell icon. At the bottom left, there is a user profile icon with the initials "PA".



### 3. Tryck på “Claim product”



Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number) 🔍

**+ CLAIM PRODUCT**

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
Sorry, no matching records found						

Rows per page: 100 ▾ 0-0 of 0 < >

### Building administrators

PA

4. Skriv in produktens serienummer och tryck precis utanför textrutan för att bekräfta. Efter att ha klickat utanför textrutan finns det möjlighet att lägga till ytterligare serienummer på samma sätt.

The screenshot displays the Swegon web interface for a building named 'Head Office' in Stockholm, Sweden. The interface includes a navigation menu on the left, a breadcrumb trail (Home > Buildings > Head Office), and a 'GO BACK' button. The main content area shows the building name, location, and coordinates. Below this, there is a 'Products' section with a search bar and a table. A modal dialog box titled 'Claim product(s)' is open, containing instructions on how to claim a product and a text input field for the serial number. The dialog also features a 'SUBMIT' button and a 'CLAIM PRODUCT' button in the background.

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden

Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number) 🔍

Name ↑	Product type	Software version	Active alarm	Connected
Sorry, no matching records found				

Building administrators

#### Claim product(s)

Once you have activated INSIDE on your INSIDE Ready product, you can claim the product to connect it to your building and start benefiting from our digital services.

The serial number can be found on the product's internal website under the 'Communication' tab

✓ SUBMIT

+ CLAIM PRODUCT

Rows per page: 100 ▾ 0-0 of 0 < >

5. Innan du klickar Submit måste du namnge dina enheter. Tryck sedan på Submit.

Om produkten redan är ansluten till INSIDE Cloud måste du ange produktens MAC-adress för att göra anspråk på den.

The screenshot shows a web interface for managing buildings. The main heading is "Head Office Stockholm, Sweden". A "Claim product(s)" dialog box is open in the center. The dialog contains the following text:

Claim product(s) [X]

Once you have activated INSIDE on your INSIDE Ready product, you can claim the product to connect it to your building and start benefiting from our digital services.

Serial number(s)

1111111111 [X] 1122112211 [X]

The serial number can be found on the product's internal website under the 'Communication' tab

Name

The following product(s) needs a name to be able to be added to the building.

1111111111	GOLD	<input type="text" value="name *"/>
1122112211	GOLD	<input type="text" value="name *"/>

[X] SUBMIT

The background interface shows a "Products" section with a search bar and a table with columns for "Name", "Product type", "Software version", "Active alarm", and "Connected". A "+ CLAIM PRODUCT" button is visible in the top right of the background interface.

## 6. Nu har du framgångsrikt skapat upp dina produkter.

The screenshot displays the Swegon web interface for a building named 'Head Office' in Stockholm, Sweden. The interface includes a navigation menu on the left, a breadcrumb trail at the top, and a main content area. The main content area shows the building name, location, and coordinates. Below this, there is a 'Products' section with a search bar and a '+ CLAIM PRODUCT' button. A table lists two products, GOLD1 and GOLD2, with their respective serial numbers and connection status. The table has columns for Name, Product type, Building, Serial number, Software version, Active alarm, and Connected. The 'Connected' column shows red dots for both products. At the bottom of the table, there is a pagination control showing 'Rows per page: 100' and '1-2 of 2'. Below the table, there is a 'Building administrators' section which is currently empty.

Home > Buildings > Head Office

← GO BACK

### Head Office

Stockholm, Sweden

Latitude: 59.32576641998  
Longitude: 18.070390739956

#### Products

Search (name, serial number)

[+ CLAIM PRODUCT](#)

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >

#### Building administrators

7. Om dina produkter är fränkopplade (enligt bild nedan) måste du kontrollera att Swegon INSIDE är aktiverat på produkten och att den har giltigt certifikat (INSIDE Ready).

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number)

+ CLAIM PRODUCT

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >

### Building administrators



PA



**Om din produkt saknar giltigt certifikat:**  
Så här gör du din produkt INSIDE Ready  
(Retrofit)


# Se till att du har SW 2.42 eller senare

## Retrofit



# Aktivera Swegon INSIDE på HMI/Web


## Retrofit



Gå till "Kommunikation"

Kontrollera att följande fält är korrekt ifyllda:

- IP-adress, nätmask, standardgateway, primär DNS
- Produktens serienummer





1. Gå till din byggnad och klicka på den produkt som du vill göra INSIDE Ready.

Home > Buildings > Head Office

← GO BACK

## Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

### Products

Search (name, serial number)

+ CLAIM PRODUCT


Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 ▾ 1-2 of 2 < >

### Building administrators

PA

## 2. Tryck på knappen “MAKE INSIDE READY”.



Home > Buildings > Head Office > Product: GOLD1

← GO BACK

**GOLD1**  
Not connected ●  
Software version: -  
Serial number: 1111111111


+ MAKE INSIDE READY EDIT NAME

Reports

Active alarms


PA

### 3. Skriv in produktens MAC-adress och tryck på "Submit".



The screenshot shows a web interface for a product named 'GOLD1'. The breadcrumb navigation at the top reads: Home > Organisations > Company Name > Building: Head Office > Product: GOLD1. In the top right corner, there are two buttons: '+ MAKE INSIDE READY' and 'EDIT NAME'. The main content area displays 'GOLD1' with a status indicator 'Not connected' (a red dot), 'Software version: -', and 'Serial number: 1111111111'. Below this, there are sections for 'Reports' and 'Active alarms', both with expandable arrows. A modal dialog box titled 'Make INSIDE Ready' is open in the center. It contains the following text: 'Making your product INSIDE Ready is the first step to benefit from Swegon's digital services. INSIDE Ready means that the product has the capability to securely connect and deliver data to the Swegon INSIDE Cloud. Read more and see the requirements [here](#)'. Below the text is a text input field labeled 'MAC address \*'. At the bottom of the dialog is a 'SUBMIT' button with a checkmark icon.

3. Kopiera ID och aktiveringskod och klistra in dem i rätt textfält i produktens HMI och tryck på "Activate".



För GOLD-enheter hittar du textfälten under "Kommunikation"

## 4. När produkterna är uppkopplade och delar data med INSIDE Cloud lyser prickarna grönt.

Home > Buildings > Head Office

← GO BACK

### Head Office

Stockholm, Sweden  
Latitude: 59.32576641998  
Longitude: 18.070390739956

#### Products

Search (name, serial number)

+ CLAIM PRODUCT

Name ↑	Product type	Building	Serial number	Software version	Active alarm	Connected
GOLD1	GOLD	Head Office	111111111			●
GOLD2	GOLD	Head Office	112211221			●

Rows per page: 100 1-2 of 2 < >

#### Building administrators

PA



# INSIDE Portal

INSIDE Portal är plattformen för alla anslutna Swegon-  
produkter och navet för Swegons digitala tjänster


# INSIDE Portal

– Navet för alla anslutna Swegon-produkter.

INSIDE Portal ger dig möjlighet att:

- Övervaka viktiga parametrar
  - Status för luftflöde, tryckfall, temperaturer etc.
  - Aktiva larm
- Skapa och exportera energirapporter
- Få övergripande insikter om AHU-aggregatets prestanda
- Enkelt aktivera ytterligare tjänster som kan öka effektiviteten i ditt system
- Bjud in portalanvändare att dela insikter och delegera åtkomstnivå

INSIDE Portal är kostnadsfri



# INSIDE Portal – Larmnotiser via email

Få larmmeddelanden till din e-post från anslutna enheter

Home > Alarm subscriptions

My alarm subscriptions

Search for any keyword

DELETE SELECTED EDIT SELECTED + ADD ALARM SUBSCRIPTION

<input type="checkbox"/>	Product name	Notify at (severity)	Building name	City	Country	Product type	Organisation
<input type="checkbox"/>	Kv Målet 1, Umeå	A B	Swegon Umeå	Umeå	Sweden	SuperWISE	Swegon
<input type="checkbox"/>	Åbyhøj GOLD	A B	Swegon Åbyhøj	Åbyhøj	Denmark	GOLD	Swegon Denmark
<input type="checkbox"/>	Zeta Sky Hi R7 (R32)	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	Titan Sky Hi R0 HP	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	GEYSER Sky R0 (R290)	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	Epsilon Sky Hi	A	Swegon Cantarana	Cantarana	Italy	BlueBox Epsilon SKY	Swegon
<input type="checkbox"/>	Boställsvägen 1 Örebro	A B T	Swegon Örebro	Örebro	Sweden	SuperWISE	Swegon
<input type="checkbox"/>	SWEGON BUREAU	A B T	Swegon France Lyon	Lyon	France	SuperWISE	Swegon
<input type="checkbox"/>	Zeta Rev	A	Swegon Cantarana	Cantarana	Italy	BlueBox Chiller/Heatpump	Swegon
<input type="checkbox"/>	TA/FA 73	A B T	Swegon Kvånum	Kvånum	Sweden	GOLD	Swegon
<input type="checkbox"/>	OPEN SPACE	A	Swegon Cantarana	Cantarana	Italy	GOLD	Swegon



# INSIDE Portal - Larmnotiser via email

## Välj vilka larm du vill bli informerad om via e-post

The screenshot shows the 'Add alarm subscriptions' dialog box in the Swegon INSIDE Portal. The dialog is titled 'Add alarm subscriptions' and has a close button (X) in the top right corner. It contains a table with the following columns: Product name, Notify at (severity), Building name, City, Country, Product type, and Organisation. Each row in the table has radio buttons for severity levels A, B, and T. The background shows the 'My alarm subscriptions' page with a search bar and a list of existing subscriptions.

Product name	Notify at (severity)	Building name	City	Country	Product type	Organisation
	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T					
Boställsvägen 1 Örebro	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Örebro	Örebro	Sweden	SuperWISE	Swegon
SWEGON BUREAU	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon France Lyon	Lyon	France	SuperWISE	Swegon
TA/FA 73	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Kvänum	Kvänum	Sweden	GOLD	Swegon
Äbyhøj GOLD	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Äbyhøj	Äbyhøj	Denmark	GOLD	Swegon Denmark
Kv Målet 1, Umeå	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Umeå	Umeå	Sweden	SuperWISE	Swegon
TA 12	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Gothenburg	Gothenburg	Sweden	GOLD	Swegon
GOLD 2005646491	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Sundsvall	Sundsvall	Sweden	GOLD	Swegon
Swegon - Brandby	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Brandby	Brandby	Denmark	SuperWISE	Swegon Denmark
Swegon Malmö	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Malmö	Malmö	Sweden	SuperWISE	Swegon
Swegon Goteborg	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Gothenburg	Gothenburg	Sweden	SuperWISE	Swegon
LB03 Luleå	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Luleå	Luleå	Sweden	GOLD	Swegon
GOLD Umeå	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Umeå	Umeå	Sweden	GOLD	Swegon
Norrkøping kontor	<input type="radio"/> A <input type="radio"/> B <input type="radio"/> T	Swegon Norrkøping	Norrkøping	Sweden	SuperWISE	Swegon

At the bottom of the dialog, there is a 'SUBMIT' button. In the background, the 'My alarm subscriptions' page shows a search bar and a list of subscriptions with checkboxes and severity level indicators (A, B, T).

# INSIDE Portal: Översikt över anslutna enheter



Home > buildings

### Buildings

Search for building name

Name ↑	City	Country	Number of products	Organization
Swegon Borås	Borås	Sweden	1	Swegon
Swegon Cantarana	Cantarana	Italy	3	Swegon
Swegon France Lyon	Lyon	France	1	Swegon
Swegon Gembloux	Gembloux	Belgium	1	Swegon
Swegon Gothenburg	Gothenburg	Sweden	1	Swegon
Swegon Kvänum	Kvänum	Sweden	3	Swegon
Swegon Kvänum Testcenter	Kvänum	Sweden	2	Swegon
Swegon Luleå	Luleå	Sweden	1	Swegon
Swegon Malmö	Malmö	Sweden	1	Swegon
Swegon Norrköping	Norrköping	Sweden	1	Swegon
Swegon Örebro	Örebro	Sweden	1	Swegon
Swegon Stockholm	Stockholm	Sweden	1	Swegon
Swegon Tomelilla	Tomelilla	Sweden	1	Swegon
Swegon Umeå	Umeå	Sweden	1	Swegon

Rows per page: 100 ▾ 1-14 of 14 < >

Fullständig översikt över alla byggnader i din organisation

- Byggnadsnamn
- Byggnadens plats
- Antal produkter

# INSIDE Portal: Översikt över anslutna enheter



Home > buildings > Swegon Kvänum

← GO BACK

## Swegon Kvänum

Kvänum, Sweden  
Latitude: 58.2980300699508  
Longitude: 13.189557

### Products

Search (name, serial number) 🔍

Name	Product type	Building	Serial number	Software version	Active alarm	Connected
Kvänum Tellus, Casa	GOLD	Swegon Kvänum	G00403364	2.42		●
Swegon Kvänum	WISE	Swegon Kvänum	6V5M1U5CIUTPHT38WDXD	1.160.1		●
TA/FA 37	GOLD	Swegon Kvänum	G320716	2.42		●

Rows per page: 10 ▾ 1-3 of 3 < >

### Rooms

### Building administrators

FR

Fullständig översikt över Swegons produkter i varje byggnad

- Plats
- Mjukvaruversion
- Aktiva larm
- Status för anslutning

# INSIDE Portal: Övervaka prestanda

← GO BACK EDIT NAME

## GOLD RXHC 12

Connected ●  
Software version: 2.42  
Serial number: 2006392391

### Information

**AHU status**

AHU status	Damper switch off delay
<b>Supply air</b>	
Supply air	15.9 °C
Supply air flow	803.0 l/s
Supply air fan power consumption	0.6 kW
Supply air duct pressure	112.5 Pa
<b>Supply filter</b>	
Supply air internal filter	106.7 Pa
Supply air internal filter alarm	0.0 Pa
<b>Extract air</b>	
Extract air	23.0 °C
Extract air flow	800.0 l/s
Extract air duct pressure	109.3 Pa
Extract air fan power consumption	0.5 kW
<b>Extract filter</b>	
Extract air internal filter	66.5 Pa

Övervaka:

- Driftstatus
- Nyckelparametrar
- Energidata
- Larm

*Live: alltid senaste värdet*

Temperature

°C

°F

Pressure

Pa

psi

in.wc

Airflow

l/s

cfm

m³/s

m³/h

# INSIDE Portal: Övervaka prestanda

Energy	
Cool power recovery	0.0 kW
Specific fan power	1.4 kW/m <sup>3</sup> /s
Temperature efficiency	0.0 %
Heat power recovery	0.0 kW
Temperature efficiency	0.0 %
Heat exchange motor energy consumption since unit installation	0.2 MWh
Heat energy consumption since unit installation	12.0 MWh
Total Heat Cool energy consumption since unit installation	16.1 MWh
Total energy recovery since unit installation	59.6 MWh
Total air fan energy consumption since unit installation	8.4 MWh
Supply air fan energy consumption	1.3 MWh
Heat energy recovery since unit installation	59.2 MWh
Supply air fan energy consumption since unit installation	4.2 MWh
Extract air fan energy consumption	1.2 MWh
Total AHU energy consumption since unit installation	8.6 MWh
Heat exchange motor power consumption	0.0 kW
Extract air fan energy consumption since unit installation	4.2 MWh
Cool energy recovery since unit installation	0.5 MWh
Total AHU energy consumption	2.6 MWh
Heat exchange motor energy consumption	0.0 MWh
Cool energy consumption since unit installation	4.1 MWh

Alarms	
Alarm priority A triggered	0
Alarm priority B triggered	0

Detaljerad information om aktiva larm

Alarms	
Name	Raised at
Info 98:7 Extract air air handling unit filter calibration not performed	2023-07-19 07:24
Info 98:5 Supply air air handling unit filter calibration not performed	2023-07-19 07:24

Rows per page: 100 1-2 of 2

# INSIDE Portal: Energirapporter



Home > buildings > Swegon Kvänum > Product: Kvänum Tellus, Casa

Connected ●  
Software version: 2.42  
Serial number: G00403364

### Information

### Reports

CREATE REPORT   DOWNLOAD REPORT ↓   DELETE REPORT(S)

Created	Status	From	To
<input checked="" type="checkbox"/> 2023-05-29 08:10	Completed	2023-05-01	2023-05-29
<input type="checkbox"/> 2023-05-10 07:54	Completed	2023-04-01	2023-05-02
<input type="checkbox"/> 2023-04-13 08:04	Completed	2023-03-17	2023-04-13
<input type="checkbox"/> 2023-04-11 13:48	Completed	2023-04-05	2023-04-10
<input type="checkbox"/> 2023-04-07 17:56	Completed	2023-03-16	2023-04-07
<input type="checkbox"/> 2023-03-27 10:17	Completed	2023-03-20	2023-03-27
<input type="checkbox"/> 2023-03-14 10:03	Completed	2023-03-06	2023-03-13

1 row selected   Rows per page: 10 ▾   1-7 of 7 < >



### Uploads

Snabbt och enkelt att generera energirapporter

# Energy report


## Analysera prestandan

Generera energirapporter med önskat tidsintervall och detaljnivå.



# INSIDE Portal: Logga in

Länk till INSIDE Portal: <https://inside.swegon.com/>



The screenshot shows the Swegon INSIDE login interface. On the left, there is a decorative graphic of overlapping semi-circles in various colors (orange, yellow, green, blue, purple) and the text "Feel good **inside**". On the right, the login form is titled "Welcome to Swegon INSIDE". Below the title, there is a short instruction: "You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account." The form includes an "Email" input field, a "Password" input field, a "Remember Login" checkbox, and a "Forgot your password?" link. A prominent green "Log In" button is located below the password field. Below the button, there is an "OR" separator and a "Login as internal provider" button with a small green leaf icon. At the bottom of the form, there is a section titled "Don't have an account?" with a "Sign up here" link.

Feel good **inside**

**Welcome to Swegon INSIDE**

You can login using your email and password if you already have an account or login with your existing Google or LinkedIn account. Sign up as a new user if you don't have an account.


Email

Password

Remember Login    [Forgot your password?](#)

**Log In**

OR


 Login as internal provider

**Don't have an account?**


[Sign up here](#)



# Flera sätt att övervaka GOLD



# Digitala tjänster



## INSIDE Director

Kombination av BMS- och EMS-funktioner för ett komplett byggnadsbestånd.

## INSIDE Analytics & Visualiser

Analys och visualisering av inomhusklimatet.

## INSIDE Portal

Fjärrövervakning av AHU:s nyckelparametrar, aktiva larm och energiförbrukning.

**Swegon** 





Feel good **inside**